

Decomposition with respect to outputs for Boolean control networks. [★]

Yunlei Zou, Jiandong Zhu

School of Mathematical Sciences, Nanjing Normal University, Nanjing, 210023, PR China

Abstract

This paper investigates the problem of decomposition with respect to outputs for Boolean control networks (BCNs). First, with the linear expression of BCNs and the matrix semi-tensor product, some algebraic equivalent conditions for the decomposition are obtained. Second, a necessary and sufficient graphical condition for the decomposition with respect to outputs is given. Third, an effective method is proposed to reduce the computational burden in the realization of the decomposition. Finally, some examples are addressed to validate the effectiveness of the proposed method.

Key words: Boolean control networks, Decomposition with respect to outputs, Semi-tensor product, Observability.

1 Introduction

Boolean networks (BNs) are a kind of discrete dynamical systems described by logical variables and logical functions. They are first proposed by Kauffman (1969) to describe and analyze cell regulation (Albert & Othmer, 2003; Faure, Naldi, Chaouiya, & Thieffry, 2006). BNs with additional inputs and outputs are usually called Boolean control networks (BCNs), and they have been paid great attention by biologists and control theory scientists (Akutsu, Hayashida, Ching, & Ng, 2007; Cheng, 2009;). In recent years, a semi-tensor product method of BNs and BCNs was developed by Cheng and his collaborators (Cheng, 2009; Cheng & Qi, 2009; Cheng & Qi, 2010a). For a complete control theory framework of the BCNs, we refer to the book written by Cheng, Qi, and Li (2011). Based on the linear algebraic expression of BCNs, many classical problems in control theory can be generalized to BCNs such as controllability, observability, stabilization, disturbance decoupling and optimal control (Cheng & Qi, 2009; Laschov & Margaliot, 2012; Laschov, Margaliot, & Even, 2013; Fornasini & Valcher, 2013a; Fornasini & Valcher, 2013b; Cheng, 2011; Zhao, Li & Cheng, 2011). Moreover, some of these results have been further extended to different kinds of BCNs (Li, Yang, & Chu, 2014; Li & Sun, 2012; Feng, Yao, & Cui, 2013;

Li & Wang, 2012).

System decomposition is an important issue in the traditional linear control system theory, which makes clear the observable and controllable components of a system. An interesting topic is ascertaining whether there exists a similar system decomposition for BCNs. As a matter of fact, this topic has been discussed by Cheng, Li and Qi (2010), where the controllable normal form, the observable normal form and the Kalman decomposition form of BCNs are presented with the state-space analysis method (Cheng & Qi, 2010b). The state space of an n -dimensional BCN is defined as the set of all logical functions with respect to the n logical variables. Since the cardinal of the state space of an n -dimensional BCN is 2^{2^n} , generally speaking, the computational burden of state space method is very heavy for large n although it displays great advantage in theoretical analysis. Furthermore, some additional regularity assumptions are imposed on the system model for achieving those decompositions.

In our recent paper Zou & Zhu (2014), we have proposed the *decomposition with respect to inputs* for BCNs, which is just the controllable normal form proposed by Cheng, Li and Qi (2010) under the regularity assumption on the largest uncontrollable subspace. But we did not use any concepts of state spaces. A main contribution of Zou & Zhu (2014) lies in that the system decomposition can be realized without the regularity condition on the largest uncontrollable subspace. Moreover, a graphical condition and a constructive algorithm for the decomposition

[★] The research is supported in part by National Natural Science Foundation (NNSF) of China under Grants 11271194, 61273115, 61074115 and 10701042.

Email addresses: zouy10903@163.com (Yunlei Zou),
jiandongzhu@njnu.edu.cn (Jiandong Zhu).

with respect to inputs are proposed. Then, a natural idea is reconsidering the observable normal form and the Kalman decomposition form for BCNs.

In this paper, we consider the decomposition with respect to outputs in the framework of the linear algebraic representation of BCNs. First, some necessary and sufficient algebraic conditions for the decomposition with respect to outputs are proposed. Next, an equivalent graphical condition for the decomposition with respect to outputs is derived. As the graphical condition is satisfied, a constructive coordinate transformation to realize the decomposition is obtained. Then, a method is proposed to reduce the computational burden in realizing the decomposition with respect to outputs. Finally, some examples are analyzed with our method.

We organize this paper as follows. In section 2, some preliminaries and problem statement are provided. In section 3, some algebraic conditions for the decomposition with respect to outputs are presented. In section 4, a graphical condition is obtained. In Section 5, a computation method is given. Finally, Section 6 gives a brief conclusion.

2 Preliminaries and Problem Statement

Let $\mathcal{D} = \{\text{True} = 1, \text{False} = 0\}$. Consider a BCN described by the logical equations

$$\begin{aligned} x_1(t+1) &= f_1(x_1(t), \dots, x_n(t), u_1(t), \dots, u_m(t)), \\ &\vdots \\ x_n(t+1) &= f_n(x_1(t), \dots, x_n(t), u_1(t), \dots, u_m(t)), \\ y_1(t) &= h_1(x_1(t), \dots, x_n(t)), \\ &\vdots \\ y_p(t) &= h_p(x_1(t), \dots, x_n(t)), \end{aligned} \quad (1)$$

where the state variables x_i , the output variables y_i and the controls u_i take values in $\mathcal{D}$, $f_i : \mathcal{D}^{n+m} \rightarrow \mathcal{D}$ and $h_i : \mathcal{D}^n \rightarrow \mathcal{D}$ are logical functions.

Consider the logical mapping $G : \mathcal{D}^n \rightarrow \mathcal{D}^n$ defined by

$$\begin{aligned} z_1 &= g_1(x_1, x_2, \dots, x_n), \\ z_2 &= g_2(x_1, x_2, \dots, x_n), \\ &\vdots \\ z_n &= g_n(x_1, x_2, \dots, x_n). \end{aligned} \quad (2)$$

If $G : \mathcal{D}^n \rightarrow \mathcal{D}^n$ is a bijection, it is called a logical coordinate transformation.

We say that BCN (1) is *decomposable with respect to outputs of order $n - s$* , if there exists a logical coordinate transformation (2), such that (1) becomes

$$\begin{aligned} z_1(t+1) &= \hat{f}_1(z_1(t), \dots, z_s(t), u_1(t), \dots, u_m(t)), \\ &\vdots \\ z_s(t+1) &= \hat{f}_s(z_1(t), \dots, z_s(t), u_1(t), \dots, u_m(t)), \\ z_{s+1}(t+1) &= \hat{f}_{s+1}(z_1(t), \dots, z_n(t), u_1(t), \dots, u_m(t)), \\ &\vdots \\ z_n(t+1) &= \hat{f}_n(z_1(t), \dots, z_n(t), u_1(t), \dots, u_m(t)), \\ y_1(t) &= \hat{h}_1(z_1(t), \dots, z_s(t)), \\ &\vdots \\ y_p(t) &= \hat{h}_p(z_1(t), \dots, z_s(t)). \end{aligned} \quad (3)$$

BCN (3) is called a *decomposition with respect to outputs of order $n - s$* . A decomposition with respect to outputs of the maximum order is called the *maximum decomposition with respect to outputs*. We say that BCN (1) is *undecomposable with respect to outputs* if the order of the maximum decomposition with respect to outputs is 0.

Denote the real number field by $\mathbf{R}$ and the set of all the $m \times n$ real matrices by $\mathbf{R}_{m \times n}$. Let $\text{Col}(A)$ be the set of all the columns of matrix A and denote the i th column of A by $\text{Col}_i(A)$. Set $\Delta_k = \{\delta_k^i | i = 1, 2, \dots, k\}$, where $\delta_k^i = \text{Col}_i(I_k)$ with I_k the $k \times k$ identity matrix. For simplicity, we denote $\Delta := \Delta_2 = \{\delta_2^1, \delta_2^2\}$. A matrix $L \in \mathbf{R}_{m \times n}$ is called a logical matrix if $\text{Col}(L) \subset \Delta_m$. Obviously, the logical matrix L satisfies $\mathbf{1}_m^T L = \mathbf{1}_n^T$, where $\mathbf{1}_n$ denote the n -dimensional column vector whose entries are all equal to 1. The set of all the $m \times r$ logical matrices is denoted by $\mathcal{L}_{m \times r}$. For simplicity, we denote the logical matrix $L = [\delta_m^{i_1}, \delta_m^{i_2}, \dots, \delta_m^{i_r}]$ by $\delta_m[i_1, i_2, \dots, i_r]$. Set $A \in \mathbf{R}_{m \times n}$, $B \in \mathbf{R}_{p \times q}$, and $\alpha = \text{lcm}(n, p)$ be the least common multiple of n and p . The left semi-tensor product of A and B is defined as (Cheng, Qi, & Li, 2011):

$$A \ltimes B = (A \otimes I_{\frac{\alpha}{n}})(B \otimes I_{\frac{\alpha}{p}}),$$

where $\otimes$ is the Kronecker product. Obviously, the left semi-tensor product is a generalization of the traditional matrix product. So $A \ltimes B$ can be written as AB . To express the logical equations with linear algebraic method, elements in $\mathcal{D}$ are identified with vectors $\text{True} \sim \delta_2^1$ and $\text{False} \sim \delta_2^2$ (Cheng, Qi, & Li, 2011).

Proposition 1. (Cheng & Qi, 2010a) *Let x_i and u_i take values in Δ and denote $x = \ltimes_{i=1}^n x_i$, $y = \ltimes_{i=1}^p y_i$, $u = \ltimes_{i=1}^m u_i$. Then the BCN (1) can be expressed in the algebraic form*

$$x(t+1) = Lu(t)x(t), \quad y(t) = Hx(t), \quad (4)$$

where $L \in \mathcal{L}_{2^n \times 2^{n+m}}$ and $H \in \mathcal{L}_{2^p \times 2^n}$.

Let $z = Tx$ be the algebraic form of logical coordinate transformation (2), where T is a permutation matrix. Set $z^{[1]} = \ltimes_{i=1}^s z_i$ and $z^{[2]} = \ltimes_{i=s+1}^n z_i$. Then the decom-

position form (3) can be rewritten in the algebraic form

$$\begin{aligned} z^{[1]}(t+1) &= G_1 u(t) z^{[1]}(t), \\ z^{[2]}(t+1) &= G_2 u(t) z(t), \\ y(t) &= M z^{[1]}(t), \end{aligned} \quad (5)$$

where $G_1 \in \mathcal{L}_{2^s \times 2^{s+m}}$, $G_2 \in \mathcal{L}_{2^{n-s} \times 2^{n+m}}$ and $M \in \mathcal{L}_{2^p \times 2^s}$.

For the BCN (1) with algebraic form (4), the *problem of decomposition with respect to outputs* is to find a coordinate transformation matrix T such that (4) has the form (5). The *problem of maximum decomposition with respect to outputs* is to find a coordinate transformation matrix T such that the decomposition with respect to outputs has the maximum order $n - s$.

In Cheng, Li and Qi (2010), the observable normal form of a BCN is proposed. Here, we rewrite the result in the algebraic form as follows.

Proposition 2. (Cheng, Li & Qi, 2010) *Consider BCN (1) with the algebraic form (4). Assume the largest unobservable subspace $\mathcal{O}_c$ is a regular subspace with $\{\tilde{z}_{\tilde{s}+1}, \tilde{z}_{\tilde{s}+2}, \dots, \tilde{z}_n\}$ as its basis. Then, under the coordinate transformation $\tilde{z} = \tilde{T}x$, the BCN (4) becomes*

$$\begin{aligned} \tilde{z}^{[1]}(t+1) &= \tilde{G}_1 u(t) \tilde{z}^{[1]}(t), \\ \tilde{z}^{[2]}(t+1) &= \tilde{G}_2 u(t) \tilde{z}(t), \\ y(t) &= \tilde{M} \tilde{z}^{[1]}(t), \end{aligned} \quad (6)$$

where $\tilde{z}^{[1]} = \times_{i=1}^{\tilde{s}} \tilde{z}_i$, $\tilde{z}^{[2]} = \times_{i=\tilde{s}+1}^n \tilde{z}_i$, $\tilde{G}_1 \in \mathcal{L}_{2^{\tilde{s}} \times 2^{\tilde{s}+m}}$, $\tilde{G}_2 \in \mathcal{L}_{2^{n-\tilde{s}} \times 2^{n+m}}$ and $\tilde{M} \in \mathcal{L}_{2^p \times 2^{\tilde{s}}}$. The decomposition form (6) is called the observable normal form of (4).

A natural question is whether the defined maximum decomposition with respect to outputs and the observable normal form proposed by Cheng, Li and Qi (2010) are the same one. Actually, with the regularity assumption, they are the same one.

For the basic concepts of the state-space method mentioned above, please refer to Cheng & Qi (2010) and Cheng, Li, & Qi (2010b). Comparing (5) with (6), we find that the maximum decomposition with respect to outputs and the observable normal form have the same structure.

Proposition 3. *Assume that the largest unobservable subspace $\mathcal{O}_c$ is regular, then (5) is a maximum decomposition with respect to outputs if and only if it is an observable normal form described by Proposition 2.*

Proof. Assume that (5) is a maximum decomposition with respect to outputs of order $n - s$. We first prove that $s = \tilde{s}$. On the one hand, by the definition of the maximum decomposition with respect to outputs, we have

$n - s \geq n - \tilde{s}$, i.e. $s \leq \tilde{s}$. On the other hand, from the definition of largest unobservable subspace, it follows that

$$z_{s+1}, \dots, z_n \in \mathcal{O}_c = \mathcal{F}(\tilde{z}_{\tilde{s}+1}, \tilde{z}_{\tilde{s}+2}, \dots, \tilde{z}_n). \quad (7)$$

Thus, (7) implies that $n - s \leq n - \tilde{s}$, namely $s \geq \tilde{s}$. Therefore, we have proved that $s = \tilde{s}$, which implies that (6) is a maximum decomposition with respect to outputs of system (4). Conversely, by $\tilde{s} = s$, (7) and Theorem 13 of Cheng, Li, & Qi (2010), we obtain that $\{z_{s+1}, \dots, z_n\}$ is a regular basis of $\mathcal{O}_c$, that is, (5) is an observable normal form. $\square$

Remark 1. *Proposition 3 implies that the decomposition with respect to outputs is a generalization of the observable normal form. From the proof of Proposition 3, we see that, if the largest unobservable subspace $\mathcal{O}_c$ is regular, then $z^{[2]}$ and $\tilde{z}^{[2]}$ can be logically expressed in terms of each other, i.e. there exists a logical matrix R such that $(\mathbf{1}_{2^s}^T \otimes I_{2^{n-s}})T = R\tilde{T}^T(\mathbf{1}_{2^s} \otimes I_{2^{n-s}})$, i.e.*

$$R = \frac{1}{2^s}(\mathbf{1}_{2^s}^T \otimes I_{2^{n-s}})T\tilde{T}^T(\mathbf{1}_{2^s} \otimes I_{2^{n-s}}). \quad (8)$$

If there exist two maximum decompositions with respect to outputs described by (5) and (6) respectively such that the right side of (8) is not a logical matrix, then the largest uncontrollable subspace is not regular.

3 Algebraic conditions for the decomposability with respect to outputs

In this section, based on the definition of the decomposability with respect to outputs, we derive some equivalent algebraic conditions.

Lemma 1. *Assume that $M_1, M_2, \dots, M_l \in \mathbf{R}_{m \times n}$ are non-negative matrices satisfying $\mathbf{1}_m^T M_k = \mathbf{1}_n^T$ for every $k = 1, 2, \dots, l$. If $M_1 + M_2 + \dots + M_l = lG$, with G being a logical matrix, then $M_1 = M_2 = \dots = M_l = G$.*

Swap matrix $W_{[m,n]}$ is an $mn \times mn$ logical matrix, defined as $W_{[m,n]} = [I_n \otimes \delta_m^1, I_n \otimes \delta_m^2, \dots, I_n \otimes \delta_m^m]$.

Lemma 2. (Cheng, Qi, & Li, 2011) *Let $W_{[m,n]} \in \mathbf{R}_{mn \times mn}$ be a swap matrix. Then $W_{[m,n]}^T = W_{[m,n]}^{-1} = W_{[n,m]}$ and $W_{[m,1]} = W_{[1,m]} = I_m$, where I_m is an identity matrix.*

Lemma 3. (Cheng, Qi, & Li, 2011) *Let $A \in \mathbf{R}_{m \times n}$, $B \in \mathbf{R}_{p \times q}$. Then $W_{[m,p]}(A \otimes B)W_{[q,n]} = (B \otimes A)$.*

Theorem 1. *Consider BCN (1) with the algebraic form (4). Let $L = [L_1, L_2, \dots, L_{2^m}]$, where $L_i \in \mathcal{L}_{2^n \times 2^n}$. Then the following statements are equivalent:*

(i) *the system (1) is decomposable with respect to outputs with order $n - s$;*

(ii) there exist a permutation matrix $T \in \mathcal{L}_{2^n \times 2^n}$, logical matrices $G_1 \in \mathcal{L}_{2^s \times 2^{m+s}}$ and $M \in \mathcal{L}_{2^p \times 2^s}$ such that

$$(I_{2^s} \otimes \mathbf{1}_{2^{n-s}}^T)TL(I_{2^m} \otimes T^T) = G_1(I_{2^{m+s}} \otimes \mathbf{1}_{2^{n-s}}^T), \quad (9)$$

$$HT^T = M(I_{2^s} \otimes \mathbf{1}_{2^{n-s}}^T). \quad (10)$$

(iii) there exist a permutation matrix $T \in \mathcal{L}_{2^n \times 2^n}$, $G_1 = [G_{11}, G_{12}, \dots, G_{12^m}] \in \mathcal{L}_{2^s \times 2^{m+s}}$ and $M \in \mathcal{L}_{2^p \times 2^s}$ such that

$$QL_i = G_{1i}Q \quad \text{and} \quad H = MQ \quad (11)$$

hold for each $i = 1, 2, \dots, 2^m$, where $Q = (I_{2^s} \otimes \mathbf{1}_{2^{n-s}}^T)T$ and $G_{1i} \in \mathcal{L}_{2^s \times 2^s}$;

(iv) there exists a permutation matrix $T \in \mathcal{L}_{2^n \times 2^n}$ such that

$$QL_iQ^T/2^{n-s} \quad \text{and} \quad HQ^T/2^{n-s} \quad (12)$$

are logical matrices, where $Q = (I_{2^s} \otimes \mathbf{1}_{2^{n-s}}^T)T$.

Proof. (i) $\Leftrightarrow$ (ii) Assume that BCN (1) is decomposable with respect to outputs of order $n - s$. Then (3) can be converted in (5). By (3), we have

$$\begin{aligned} z^{[1]}(t+1) &= (I_{2^s} \otimes \mathbf{1}_{2^{n-s}}^T)z(t+1) \\ &= (I_{2^s} \otimes \mathbf{1}_{2^{n-s}}^T)TL(I_{2^m} \otimes T^T)u(t)z(t), \end{aligned} \quad (13)$$

$$y(t) = HT^T z^{[1]}(t)z^{[2]}(t). \quad (14)$$

By (5), we have

$$z^{[1]}(t+1) = G_1(I_{2^{m+s}} \otimes \mathbf{1}_{2^{n-s}}^T)u(t)z(t), \quad (15)$$

$$y(t) = M(I_{2^s} \otimes \mathbf{1}_{2^{n-s}}^T)z^{[1]}(t)z^{[2]}(t). \quad (16)$$

From (13) and (15), we get (9). From (14) and (16), we get (10). Conversely, with the similar procedure, it follows from (9) and (10) that (5) holds. Thus (i) is proved. (ii) $\Rightarrow$ (iii) Multiplying (9) on the right by $I_{2^m} \otimes T$ yields

$$\begin{aligned} QL &= G_1(I_{2^m} \otimes ((I_{2^s} \otimes \mathbf{1}_{2^{n-s}}^T)T)) \\ &= [G_{11}, G_{12}, \dots, G_{12^m}](I_{2^m} \otimes Q) \\ &= [G_{11}Q, G_{12}Q, \dots, G_{12^m}Q], \end{aligned} \quad (17)$$

which implies $QL_i = G_{1i}Q$. Multiplying (10) on the right by T gives $H = MQ$.

(iii) $\Rightarrow$ (iv) A straightforward calculation shows that

$$QQ^T = (I_{2^s} \otimes \mathbf{1}_{2^{n-s}}^T)TT^T(I_{2^s} \otimes \mathbf{1}_{2^{n-s}}) = 2^{n-s}I_{2^s}.$$

Thus, it follows from (11) that

$$G_{1i} = QL_iQ^T/2^{n-s} \quad \text{and} \quad M = HQ^T/2^{n-s}. \quad (18)$$

Thus the matrices in (12) are logical matrices.

(iv) $\Rightarrow$ (iii) Denote the logical matrices in (12) by G_{1i} and M respectively. Let

$$QL_iT^TW_{[2^{n-s}, 2^s]} = [P_1, P_2, \dots, P_{2^{n-s}}], \quad (19)$$

where $P_i \in \mathcal{L}_{2^s \times 2^s}$ are non-negative matrices. By (19), Lemmas 2 and 3, we have

$$\begin{aligned} G_{1i} &= QL_iQ^T/2^{n-s} \\ &= [P_1, P_2, \dots, P_{2^{n-s}}]W_{[2^s, 2^{n-s}]}TQ^T/2^{n-s} \\ &= [P_1, P_2, \dots, P_{2^{n-s}}](\mathbf{1}_{2^{n-s}} \otimes I_{2^s})/2^{n-s}, \end{aligned}$$

that is,

$$\sum_{k=1}^{2^{n-s}} P_k = 2^{n-s}G_{1i}. \quad (20)$$

Multiplying (19) on the left by $\mathbf{1}_{2^s}^T$ yields

$$\mathbf{1}_{2^s}^T[P_1, P_2, \dots, P_{2^{n-s}}] = \mathbf{1}_{2^n}^T W_{[2^{n-s}, 2^s]} = \mathbf{1}_{2^n}^T, \quad (21)$$

namely, $\mathbf{1}_{2^s}^T P_k = \mathbf{1}_{2^s}^T$ for every $k = 1, 2, \dots, 2^{n-s}$. Thus, from Lemma 1 and (20), it follows that $P_k = G_{1i}$. Considering (19), we have

$$QL_iT^TW_{[2^{n-s}, 2^s]} = G_{1i}(\mathbf{1}_{2^{n-s}}^T \otimes I_{2^s}). \quad (22)$$

Thus

$$QL_iT^T = G_{1i}(I_{2^s} \otimes \mathbf{1}_{2^{n-s}}^T), \quad (23)$$

which implies $QL_i = G_{1i}Q$. With a same procedure above, we obtain $H = MQ$.

(iii) $\Rightarrow$ (ii) The proof is trivial. $\square$

4 A graphical condition for the decomposability with respect to outputs

Consider BCN (4) with $L = [L_1, L_2, \dots, L_{2^m}] \in \mathcal{L}_{2^n \times 2^{n+m}}$. Each logical matrix L_j can be regarded as an adjacency matrix of a directed graph $\mathcal{G}_j$. The vertex set of $\mathcal{G}_j$ is $A = \{1, 2, 3, \dots, 2^n\}$, and $\mathcal{G}_j$ has a directed edge (q, k) if and only if $(L_j)_{kq} \neq 0$. We say that k is an *out-neighbor* of q with respect to $\mathcal{G}_j$ if $(L_j)_{kq} \neq 0$. We denote the *out-neighborhood* of set S in graph $\mathcal{G}_j$ by $\mathcal{N}^j(S)$.

Definition 1. Let A be the vertex set of a graph $\mathcal{G}$, and $\Phi_l, l = 1, 2, \dots, \mu$ be subsets of A . $\{\Phi_l\}_{l=1}^\mu$ is called a *vertex partition* of A , if $\cup_{l=1}^\mu \Phi_l = A$ and $\Phi_i \cap \Phi_j = \emptyset$ for any $i \neq j$. A vertex partition $\{S_l\}_{l=1}^\mu$ of A is called an *equal vertex partition* if $|S_l| = |A|/\mu$ for every $l = 1, 2, \dots, \mu$.

In Zou & Zhu (2014), the concept of *perfect equal vertex partition* (PEVP) is proposed for the decomposition with respect to inputs. Here, we further extend this concept to deal with the decomposition with respect to outputs.

Definition 2. Consider the set $\{\mathcal{G}_j\}_{j=1}^{2^m}$ composed of 2^m digraphs with the common vertex set A . Assume that different colors are assigned to all the vertices of A . An *equal vertex partition* $\mathcal{S} = \{S_l\}_{l=1}^\mu$ of A is called a *common*




Fig.1. CC-PEVP of two graphs $\mathcal{G}_1$ and $\mathcal{G}_2$.

concolorous perfect equal vertex partition (CC-PEVP) of $\{\mathcal{G}_j\}_{j=1}^{2^m}$ if

- (i) $\mathcal{S}$ is perfect for each $j = 1, 2, \dots, 2^m$, i.e. for any given l and j , there exists an α_l^j such that $\mathcal{N}^j(S_l) \subset S_{\alpha_l^j}$;
- (ii) for any given $l = 1, 2, \dots, \mu$, all the vertices in S_l have the same color.

We give a simple example shown in Fig. 1 to explain Definition 2 intuitively. In Fig. 1, each vertex has red or green color. The digraph with blue edges is denoted by $\mathcal{G}_1$ and the other one with black edges is denoted by $\mathcal{G}_2$. Obviously, $\{S_1, S_2, S_3, S_4\}$ shown in Fig.1 forms an equal vertex partition and each S_l contains vertices of the same color. Moreover, from Fig.1, we have

$$\begin{aligned} \mathcal{N}^1(S_1) &= \mathcal{N}^1(S_2) = \{3\} \subset S_1, \quad \mathcal{N}^1(S_3) = \mathcal{N}^1(S_4) = \{1\} \subset S_2, \\ \mathcal{N}^2(S_1) &= \mathcal{N}^2(S_2) = \mathcal{N}^2(S_3) = \mathcal{N}^2(S_4) = \{4, 5\} \subset S_4. \end{aligned}$$

Therefore, by Definition 2, $\{S_1, S_2, S_3, S_4\}$ is a CC-PEVP of $\{\mathcal{G}_1, \mathcal{G}_2\}$.

Based on Definition 2, we propose an equivalent graphical condition for the decomposability with respect to outputs in the following theorem.

Theorem 2. Consider the BCN (1) with algebraic form (4). Let $L = [L_1, L_2, \dots, L_{2^m}]$ with each $L_j \in \mathcal{L}_{2^n \times 2^n}$. Denote by A the common vertex set of $\{\mathcal{G}_j\}_{j=1}^{2^m}$, where each $\mathcal{G}_j$ is induced by L_j . Color all the vertices in A in such a way that any two vertices μ and λ are of the same color if and only if $H\delta_{2^n}^\mu = H\delta_{2^n}^\lambda$. Then BCN (1) is decomposable with respect to outputs with order $n - s$ if and only if $\{\mathcal{G}_j\}_{j=1}^{2^m}$ has a CC-PEVP $\{S_l\}_{l=1}^{2^s}$ with $|S_l| = 2^{n-s}$.

Before the proof of Theorem 2, we give an intuitive explanation on the motivation. From the decomposition form (3), it follows that, as $z_1, \dots, z_s$ are fixed, the set

$$S_{z_1 \dots z_s} = \{(z_1, \dots, z_s, z_{s+1}, \dots, z_n) \mid z_j \in \{0, 1\}, s+1 \leq j \leq n\}$$

has 2^{n-s} states and these states have the same output. Then the family

$$\{S_{z_1 \dots z_s} \mid z_j \in \{0, 1\}, j = 1, 2, \dots, s\}, \quad (24)$$

forms a concolorous equal partition of all the 2^n states. From the algebraic representation (5), it follows that

$z^{[1]}(t+1) = G_{1j}z^{[1]}(t)$ for any fixed $u(t) = \delta_{2^m}^j$, i.e. the state $z(t)$ transmits from one $S_{z_1 \dots z_s}$ to another for any given graph $\mathcal{G}_j$. This is just why we propose the concept of CC-PEVP and try to reveal the relationship between CC-PEVP and the decomposition with respect to outputs.

Proof of Theorem 2. (Necessity) By Theorem 1, there exist a permutation matrix $T \in \mathcal{L}_{2^n \times 2^n}$ and logical matrices $G_{1j} \in \mathcal{L}_{2^s \times 2^s}$ ($j = 1, 2, \dots, 2^m$), $M \in \mathcal{L}_{2^p \times 2^s}$ such that the equalities in (11) hold for each $j = 1, 2, \dots, 2^m$. Set

$$Q = (I_{2^s} \otimes \mathbf{1}_{2^{n-s}}^T)T = \delta_{2^s}[i_1, \dots, i_{2^n}]. \quad (25)$$

Thus, (11) can be rewritten as

$$\delta_{2^s}[i_1, \dots, i_{2^n}]L_j = G_{1j}\delta_{2^s}[i_1, \dots, i_{2^n}], \quad (26)$$

$$H = M\delta_{2^s}[i_1, \dots, i_{2^n}]. \quad (27)$$

Let $S_l = \{q \mid i_q = l\}$. Then $\{S_l\}_{l=1}^{2^s}$ is an equal vertex partition of A with $|S_l| = 2^{n-s}$. For any l , we have that

$$\exists \alpha_l^j, \beta_l, \text{ s.t. } G_{1j}\delta_{2^s}^l = \delta_{2^s}^{\alpha_l^j}, \quad M\delta_{2^s}^l = \delta_{2^p}^{\beta_l}. \quad (28)$$

For any $k \in \mathcal{N}^j(S_l)$, there exists $q \in S_l$, i.e. $i_q = l$, such that $\text{Col}_q(L_j) = \delta_{2^n}^k$. Then, by (28), we have

$$\delta_{2^s}^{i_k} = \delta_{2^s}[i_1, \dots, i_{2^n}]\text{Col}_q(L_j) = G_{1j}\delta_{2^s}^{i_q} = G_{1j}\delta_{2^s}^l = \delta_{2^s}^{\alpha_l^j}. \quad (29)$$

Thus $i_k = \alpha_l^j$, which implies $k \in S_{\alpha_l^j}$. Therefore, we have $\mathcal{N}^j(S_l) \subset S_{\alpha_l^j}$. Moreover, for every $k \in S_l$ ($i_k = l$),

$$H\delta_{2^n}^k = M\delta_{2^s}^{i_k} = M\delta_{2^s}^l = \delta_{2^p}^{\beta_l},$$

which implies that all the vertices in S_l have the same color.

(Sufficiency) Since $\{S_l\}_{l=1}^{2^s}$ is a CC-PEVP, by Definition 1 and the definition of the coloring, we have that

$$\forall 1 \leq l \leq 2^s, 1 \leq j \leq 2^m, \exists \alpha_l^j, \text{ s.t. } \mathcal{N}^j(S_l) \subset S_{\alpha_l^j} \quad (30)$$

and

$$\forall 1 \leq l \leq 2^s, \exists \beta_l, \text{ s.t. } \forall q \in S_l, H\delta_{2^n}^q = \delta_{2^p}^{\beta_l}. \quad (31)$$

For any $q \in S_l$ ($l = 1, 2, \dots, 2^s$), let $i_q = l$. We denote $Q = \delta_{2^s}[i_1, \dots, i_{2^n}]$. Since $|S_l| = 2^{n-s}$, there exists a permutation matrix T such that $(I_{2^s} \otimes \mathbf{1}_{2^{n-s}}^T)T = Q$. For any $l \in \{1, 2, \dots, 2^s\}$, we have

$$\begin{aligned} \text{Col}_l(QL_jQ^T) &= QL_j\text{Col}_l(Q^T) = QL_j \sum_{q \in S_l} \delta_{2^n}^q \\ &= \sum_{q \in S_l} Q\text{Col}_q(L_j). \end{aligned} \quad (32)$$

Since L_j is a logical matrix, we can let $\text{Col}_q(L_j) = \delta_{2^n}^{k_q}$, i.e. $k_q \in \mathcal{N}^j(\{q\})$. Thus it follows from (32) and (30) that

$$\begin{aligned} \text{Col}_l(Q L_j Q^T) &= \sum_{q \in S_l} Q \delta_{2^n}^{k_q} = \sum_{q \in S_l} \delta_{2^s}^{i_{k_q}} \\ &= \sum_{q \in S_l} \delta_{2^s}^{\alpha_l^j} \quad (k_q \in N^j(\{q\}) \subset N^j(S_l) \subset S_{\alpha_l^j}) \\ &= 2^{n-s} \delta_{2^s}^{\alpha_l^j}. \end{aligned} \quad (33)$$

From (31), it follows that

$$\begin{aligned} \text{Col}_l(H Q^T) &= H \text{Col}_l(Q^T) = \sum_{q \in S_l} H \delta_{2^n}^q \\ &= \sum_{q \in S_l} \delta_{2^s}^{\beta_l} = 2^{n-s} \delta_{2^s}^{\beta_l}. \end{aligned} \quad (34)$$

By (33) and (34), both $Q L_j Q^T / 2^{n-s}$ and $H Q^T / 2^{n-s}$ are logical matrices. Therefore, by (iv) of Theorem 1, the sufficiency is proved. $\square$

From the sufficiency proof of Theorem 2, we see that, if a CC-PEVP $\{S_l\}_{l=1}^{2^s}$ is given, a constructive procedure to calculate the transformation matrix T is obtained as follow:

- (i) let $i_q = l$ for any $l = 1, 2, \dots, 2^s$ and $q \in S_l$;
- (ii) let $Q = \delta_{2^s}[i_1, \dots, i_{2^n}]$;
- (iii) compute permutation matrix T from

$$(I_{2^s} \otimes \mathbf{1}_{2^{n-s}}^T) T = Q.$$

To display the effectiveness of Theorem 2, we reconsider Example 10.3 of Cheng, Qi, & Li (2011) and construct the coordinate transformation using the graphical method.

Example 1. Consider the following system

$$\begin{aligned} x_1(t+1) &= x_3(t) \vee u(t), \\ x_2(t+1) &= (x_1(t) \wedge \neg x_3(t)) \vee (\neg x_1(t) \wedge (x_3(t) \leftrightarrow u(t))), \\ x_3(t+1) &= x_3(t) \rightarrow u(t), \\ y(t) &= (x_1(t) \leftrightarrow x_3(t)) \rightarrow (x_2(t) \bar{\vee} x_3(t)). \end{aligned} \quad (35)$$

Let $x(t) = x_1(t)x_2(t)x_3(t)$. Then we have

$$x(t+1) = L u(t) x(t), \quad y(t) = H x(t),$$

where $L = [L_1, L_2] \in \mathcal{L}_{8 \times 16}$, with

$$L_1 = \delta_8[3 \ 1 \ 3 \ 1 \ 1 \ 3 \ 1 \ 3], \quad L_2 = \delta_8[4 \ 5 \ 4 \ 5 \ 4 \ 5 \ 4 \ 5]$$

and

$$H = \delta_2[2 \ 1 \ 1 \ 1 \ 1 \ 1 \ 1 \ 2].$$

The digraphs $\mathcal{G}_1$ and $\mathcal{G}_2$ corresponding to BCN (35) is just shown in Fig.1. The vertex partition S_i ($i =$

1, 2, 3, 4) given in Fig.1 is a CC-PEVP of $\{\mathcal{G}_1, \mathcal{G}_2\}$. Thus BCN (35) is decomposable with respect to outputs of order 1. Let

$$(I_4 \otimes \mathbf{1}_2^T) T = Q = \delta_4[2 \ 3 \ 1 \ 4 \ 4 \ 1 \ 3 \ 2].$$

It follows that $T = \delta_8[3 \ 6 \ 1 \ 8 \ 7 \ 2 \ 5 \ 4]$. The coordinate transformation matrix T is the same as that given in Example 10.3 of Cheng, Qi, & Li (2011). Therefore, the decomposition with respect to outputs is obtained as

$$\begin{cases} z_1(t+1) = u(t), \\ z_2(t+1) = z_1(t) \wedge u(t), \\ z_3(t+1) = z_3(t) \rightarrow u(t). \\ y(t) = z_1(t) \rightarrow z_2(t). \end{cases}$$

5 Searching a CC-PEVP

To achieve the decomposition with respect to outputs of the maximum order $n - s$, we need to find a CC-PEVP $\{S_l\}_{l=1}^{2^s}$ of the minimum s . Since the number of all the equal vertex partitions is finite, a straightforward method is to check whether each one is a CC-PEVP or not, but the computational burden of this method is very heavy. To reduce the computational burden, we investigate some necessary conditions for the existence of a CC-PEVP.

For BCN (1) with the algebraic form (4), let

$$R_k^{j_1 j_2 \dots j_r} = \{q \mid \text{Col}_q(H L_{j_1} L_{j_2} \dots L_{j_r}) = \delta_{2^p}^k\} \quad (36)$$

for any $k = 1, 2, \dots, 2^p$, $r \geq 0$ and $1 \leq j_1, j_2, \dots, j_r \leq 2^m$. Here, $r = 0$ means that all the j_i vanish, i.e.

$$R_k = \{q \mid \text{Col}_q(H) = \delta_{2^p}^k\}.$$

From (36), we get the following result.

Lemma 4. For any given $j_1, j_2, \dots, j_r$, the family $\mathcal{R}^{j_1 j_2 \dots j_r} = \{R_k^{j_1 j_2 \dots j_r}\}_{k=1}^{2^p}$ is a partition of $A = \{1, 2, \dots, 2^n\}$. For any $q_1, q_2 \in A$, they are in the same $R_k^{j_1 j_2 \dots j_r}$ if and only if

$$\text{Col}_{q_1}(H L_{j_1} \dots L_{j_r}) = \text{Col}_{q_2}(H L_{j_1} \dots L_{j_r}).$$

Given a partition $\mathcal{R}$ of set A , for any $q_1, q_2 \in A$, we say that q_1 is equivalent to q_2 , denoted by $q_1 \stackrel{\mathcal{R}}{\sim} q_2$, if and only if there exists a $R \in \mathcal{R}$ such that $q_1, q_2 \in R$. Conversely, each equivalence relation on A induces an

associated partition $\mathcal{R}$ of set A . Therefore, by Lemma 4, we have

$$q_1 \stackrel{\mathcal{R}^{j_1 \cdots j_r}}{\sim} q_2 \Leftrightarrow \text{Col}_{q_1}(HL_{j_1} \cdots L_{j_r}) = \text{Col}_{q_2}(HL_{j_1} \cdots L_{j_r}). \quad (37)$$

Let us briefly recall some basic and well-known terms, notions and facts, without proofs, concerning partitions and equivalence relations. For details, please refer to Borůvka (1974) and Potůček (2014).

Definition 3. Let $\mathcal{U}$ and $\mathcal{V}$ be partitions of a set A . Assume that, for every $U \in \mathcal{U}$, there exists $V \in \mathcal{V}$ such that $U \subset V$. Then partition $\mathcal{U}$ is said to be a refinement of $\mathcal{V}$, which is denoted by $\mathcal{U} \sqsubset \mathcal{V}$.

Definition 4. A meet of two partitions $\mathcal{U}$ and $\mathcal{V}$ of a set A , denoted by $\mathcal{U} \sqcap \mathcal{V}$, is a set of all intersections $U \cap V$, where $U \in \mathcal{U}$ and $V \in \mathcal{V}$.

Lemma 5. Let $\mathcal{V}_1$ and $\mathcal{V}_2$ be two partitions of a set A and let $\mathcal{V} = (\mathcal{V}_1 \sqcap \mathcal{V}_2) \setminus \{\emptyset\}$. Then $\mathcal{V}$ is a partition of A satisfying $\mathcal{V} \sqsubset \mathcal{V}_1$ and $\mathcal{V} \sqsubset \mathcal{V}_2$. Moreover, if $\mathcal{U}$ is a partition of A such that $\mathcal{U} \sqsubset \mathcal{V}_1$ and $\mathcal{U} \sqsubset \mathcal{V}_2$, then $\mathcal{U} \sqsubset \mathcal{V}$.

Definition 5. The partition $\mathcal{V}$ given in Lemma 5 is called the greatest common refinement of the partitions $\mathcal{V}_1$ and $\mathcal{V}_2$ denoted by $\mathbf{gcr}(\mathcal{V}_1, \mathcal{V}_2)$.

Definition 6. The greatest common refinement of the partitions $\mathcal{V}_1, \mathcal{V}_2, \dots, \mathcal{V}_\mu$ of A is inductively defined as $\mathbf{gcr}(\mathcal{V}_1, \mathcal{V}_2, \dots, \mathcal{V}_\mu) = \mathbf{gcr}(\mathbf{gcr}(\mathcal{V}_1, \mathcal{V}_2, \dots, \mathcal{V}_{\mu-1}), \mathcal{V}_\mu)$.

Lemma 6. Let $\mathcal{W} = \mathbf{gcr}(\mathcal{V}_1, \mathcal{V}_2, \dots, \mathcal{V}_\mu)$. Then, for any $q_1, q_2 \in A$, we have

$$q_1 \stackrel{\mathcal{W}}{\sim} q_2 \Leftrightarrow (q_1 \stackrel{\mathcal{V}_i}{\sim} q_2, \quad i = 1, 2, \dots, \mu). \quad (38)$$

Now, let us come to our main result:

Proposition 4. Assume that BCN (4) with $L = [L_1, \dots, L_{2^m}]$ is decomposable with respect to outputs with order $n - s$, where each $L_i \in \mathcal{L}_{2^n \times 2^n}$. Denote by $\mathcal{G}_j$ the directed graph with the adjacency matrix L_j . Let $\mathcal{S} = \{S_l\}_{l=1}^{2^s}$ ($|S_l| = 2^{n-s}$) be a CC-PEVP of $\{\mathcal{G}_j\}_{j=1}^{2^m}$. Then

$$\mathcal{S} \sqsubset \mathcal{R}^{j_1 \cdots j_r}, \quad \forall r \geq 0, \quad \forall j_1, \dots, j_r \in \{1, 2, \dots, 2^m\}.$$

Proof. For any $l = 1, 2, \dots, 2^s$ and $q \in S_l$, let $i_q = l$. Set $Q = \delta_{2^s}[i_1, \dots, i_{2^n}]$. Then by the sufficiency proof of Theorem 2, we obtain (iv) of Theorem 1, which is equivalent to (iii) of Theorem 1. From (11), we have $H = MQ$ and

$$HL_{j_1} \cdots L_{j_r} = MQ L_{j_1} \cdots L_{j_r} = MG_{1j_1} \cdots G_{1j_r} Q \quad (39)$$

for any $1 \leq j_1, \dots, j_r \leq 2^m$. Choose $\beta_l^{j_1 j_2 \cdots j_r}$ such that

$$\delta_{2^p}^{\beta_l^{j_1 j_2 \cdots j_r}} = MG_{1j_1} \cdots G_{1j_r} \delta_{2^s}^l. \quad (40)$$

Now we are in a position to prove $S_l \subset R_{\beta_l^{j_1 j_2 \cdots j_r}}^{j_1 j_2 \cdots j_r}$. In fact, for every $k \in S_l$ ($i_k = l$), it follows from (39) that

$$\begin{aligned} \text{Col}_k(HL_{j_1} \cdots L_{j_r}) &= MG_{1j_1} \cdots G_{1j_r} Q \delta_{2^n}^k \\ &= MG_{1j_1} \cdots G_{1j_r} \delta_{2^s}^{i_k} \\ &= MG_{1j_1} \cdots G_{1j_r} \delta_{2^s}^l \\ &= \delta_{2^p}^{\beta_l^{j_1 j_2 \cdots j_r}}. \end{aligned} \quad (41)$$

Thus it follows from (36) that $k \in R_{\beta_l^{j_1 j_2 \cdots j_r}}^{j_1 j_2 \cdots j_r}$. $\square$

From Proposition 4, it seems that an infinite number of partitions need to be considered. But actually only a finite number of partitions are necessary due to the following result.

Lemma 7 (Cheng, Qi, & Zhao, 2011). Define a set of logical matrices as

$$\begin{aligned} \mathcal{H}_0 &= \{H\}, \\ \mathcal{H}_r &= \{HL_{j_1} L_{j_2}, \dots, L_{j_r} \mid j_1, j_2, \dots, j_r \in \{1, 2, \dots, 2^m\}\}, \end{aligned}$$

where $r = 1, 2, \dots$. Then there exists the minimum r^* such that $\mathcal{H}_r \subset \cup_{r=0}^{r^*} \mathcal{H}_r$ for any $r > r^*$.

Denote

$$\mathcal{H} = \mathcal{H}_0 \cup \mathcal{H}_1 \cup \dots \cup \mathcal{H}_{r^*} \quad (42)$$

and let $|\mathcal{H}| = \tau$. For convenience, we denote the τ matrices in $\mathcal{H}$ by $H_i = \delta_{2^p}[h_{i1}, h_{i2}, \dots, h_{i2^n}]$ and the corresponding partitions by $\mathcal{R}_i$ ($i = 1, 2, \dots, \tau$). By Proposition 4 and Lemma 7, we see that it is only needed to search a CC-PEVP $\{S_l\}_{l=1}^{2^s}$ from the partitions $\mathcal{R}_i$ ($i = 1, 2, \dots, \tau$). Let

$$\mathcal{O} = \begin{bmatrix} h_{11} & h_{12} & \cdots & h_{12^n} \\ h_{21} & h_{22} & \cdots & h_{22^n} \\ \vdots & \vdots & \ddots & \vdots \\ h_{\tau 1} & h_{\tau 2} & \cdots & h_{\tau 2^n} \end{bmatrix}, \quad (43)$$

which is just the observability matrix proposed in Cheng & Qi (2009).

Corollary 1. Under the conditions of Proposition 4, we have

$$\mathcal{S} \sqsubset \mathbf{gcr}(\mathcal{R}_1, \mathcal{R}_2, \dots, \mathcal{R}_\tau) =: \mathcal{C}. \quad (44)$$

By Corollary 1, we only need to search the CC-PEVP $\mathcal{S} = \{S_l\}_{l=1}^{2^s}$ of the minimum s from partition $\mathcal{C}$.

Proposition 5. For any $q_1, q_2 \in A$, we have

$$q_1 \stackrel{\mathcal{C}}{\sim} q_2 \Leftrightarrow \text{Col}_{q_1}(\mathcal{O}) = \text{Col}_{q_2}(\mathcal{O}), \quad (45)$$

where partition $\mathcal{C}$ of the vertex set A is shown in (44).

Proof. By (37), Lemma 6 and (43), the proposition is proved.

Corollary 2. If there exists a $C \in \mathcal{C}$ with odd cardinal, then BCN (4) is undecomposable with respect to outputs.

Proof. By Corollary 1, C is a union of some S_l . Since $|S_l| = 2^{n-s}$ for each l , we see that 2^{n-s} is a factor of $|C|$. Considering that $|C|$ is odd, we obtain the order $n-s = 0$. Thus BCN (4) is undecomposable with respect to outputs.

Lemma 8 (Cheng & Qi, 2009). Assume that BCN (4) is globally controllable. Then it is observable if and only if all the columns of $\mathcal{O}$ are distinct.

Corollary 3. Assume that BCN (4) is globally controllable. If (4) is observable, then it is undecomposable with respect to outputs.

Proof. From Lemma 8, it follows that $|C| = 1$ for each $C \in \mathcal{C}$. Thus the corollary is proved by Corollary 2.

Remark 2. The inverse of Corollary 3 is not correct. For example, consider a Boolean network (4) without control ($m = 0$). Let $L = \delta_4[1, 2, 3, 1]$ and $H = \delta_2[1, 1, 1, 2]$. Since $HL^i = \delta_2[1, 1, 1, 1]$ for any $i > 0$, we have that

$$\mathcal{O} = \begin{bmatrix} 1 & 1 & 1 & 2 \\ 1 & 1 & 1 & 1 \end{bmatrix},$$

which implies that $\mathcal{C} = \{\{1, 2, 3\}, \{4\}\}$. Thus the BCN is unobservable and undecomposable. However, for the traditional linear control systems, the observability and the decomposability are equivalent. This is a property of BCNs different from that of the traditional linear control systems. Hence, we prefer to call (3) the decomposition with respect to outputs instead of the observability decomposition.

To illustrate our method, we consider a practical example.

Example 2. A shift register is a cascade of flip-flops:

$$\begin{aligned} x_i(k+1) &= x_{i+1}(k), \quad (i = 1, 2, \dots, n-1), \\ x_n(k+1) &= u(k), \\ y(k) &= x_1(k), \end{aligned} \quad (46)$$

where x_i is the binary state of the i th flip-flop, u the input and y the output. Multiplying all the equations yields

$$x(k+1) = Lx(k), \quad y(k) = Hx(k),$$

where $L = [L_1, L_2] = \mathbf{1}_2^T W_{[2, 2^n]}$ with

$$\begin{aligned} L_1 &= \delta_{2^n}[1, 3, 5, \dots, 2^n-1, 1, 3, 5, \dots, 2^n-1], \\ L_2 &= \delta_{2^n}[2, 4, 6, \dots, 2^n, 2, 4, 6, \dots, 2^n] \end{aligned}$$

and

$$H = \delta_2[\overbrace{1, 1, \dots, 1}^{2^{n-1}}, \overbrace{2, 2, \dots, 2}^{2^{n-1}}].$$

A straightforward computation shows that $\mathcal{C} = \{\{i\}\}_{i=1}^{2^n}$, i.e. $|C| = 1, \forall C \in \mathcal{C}$. Thus the shift register is observable and undecomposable with respect to outputs. To give an intuitive explanation, we list the procedure for the case of $n = 3$ as follows.

$$\begin{aligned} H &= \delta_2[1, 1, 1, 1, 2, 2, 2, 2], \\ HL_i &= \delta_2[1, 1, 2, 2, 1, 1, 2, 2] \quad (i = 1, 2), \\ HL_i L_j &= \delta_2[1, 2, 1, 2, 1, 2, 1, 2] \quad (i, j = 1, 2), \\ HL_i L_j L_k &= \begin{cases} \delta_2[1, 1, 1, 1, 1, 1, 1, 1], & k = 1, \\ \delta_2[2, 2, 2, 2, 2, 2, 2, 2], & k = 2. \end{cases} \end{aligned}$$

It is easy to check that all the columns of $\mathcal{O}$ are distinct.

In order to display the procedure of finding a CC-PEVP, we reconsider the BCN given in Example 1.

Example 3. For BCN (35), we have

$$\begin{aligned} H &= \delta_2[2, 1, 1, 1, 1, 1, 1, 2], \\ HL_1 &= \delta_2[1, 2, 1, 2, 2, 1, 2, 1], \\ HL_2^2 &= HL_2 L_1 = HL_1^2 = HL_2 = \delta_2[1, 1, 1, 1, 1, 1, 1, 1], \\ HL_1 L_2 &= \delta_2[2, 2, 2, 2, 2, 2, 2, 2]. \end{aligned}$$

From the observability matrix, we have

$$\mathcal{C} = \{\{1, 8\}, \{2, 4, 5, 7\}, \{3, 6\}\}. \quad (47)$$

By (47), we first let $S_1 = \{1, 8\}$, $S_2 = \{3, 6\}$. Since $\mathcal{N}^2(S_1) = \{4, 5\}$, we let $S_3 = \{4, 5\}$ and $S_4 = \{2, 7\}$. It is easy to check that $\{S_l\}_{l=1}^4$ ($|S_l| = 2$) is the unique CC-PEVP. Thus, the system is decomposable with respect to outputs. In fact, the partition obtained here is the same one as shown in Fig.1.

A contribution of this paper lies in that the regularity assumption on the unobservable subspace proposed by Cheng, Li, & Qi (2010) is removed. To illustrate this point, we consider an example as follows.

Example 3. Consider BCN (4) with $L=[L_1, L_2] \in \mathcal{L}_{8 \times 16}$,

$$L_1 = \delta_8[6, 8, 1, 8, 7, 8, 6, 8], \quad L_2 = \delta_8[6, 8, 7, 8, 1, 8, 6, 8]$$

and $H = \delta_2[1, 1, 2, 1, 2, 1, 1, 1]$. A straightforward computation shows that

$$\mathcal{O} = \begin{bmatrix} 1 & 1 & 2 & 1 & 2 & 1 & 1 & 1 \\ 1 & 1 & 1 & 1 & 1 & 1 & 1 & 1 \end{bmatrix}. \quad (48)$$

Thus

$$\mathcal{C} = \{\{1, 2, 4, 6, 7, 8\}, \{3, 5\}\}.$$

We try to search a CC-PEVP $\mathcal{S}$ from $\mathcal{C}$. Let $S_1 = \{3, 5\}$. It is easy to check that $\mathcal{N}^1(S_1) = \mathcal{N}^2(C_2) = \{1, 7\}$. So we let $S_2 = \{1, 7\}$. Assume $S_3 = \{2, 6\}$ and $S_4 = \{4, 8\}$. Then it is easily seen that

$$\mathcal{N}^1(S_1) = \mathcal{N}^2(S_1) = \{1, 7\} = S_2,$$

$$\mathcal{N}^1(S_2) = \mathcal{N}^2(S_2) = \{6\} \subset S_3,$$

$$\mathcal{N}^1(S_3) = \mathcal{N}^2(S_3) = \{8\} \subset S_4,$$

$$\mathcal{N}^1(S_4) = \mathcal{N}^2(S_4) = \{8\} \subset S_4.$$

Furthermore, by the color of vertices, the vertices in S_i have the same output. Thus the system is decomposable with respect to outputs of the maximum order 1. From $\{S_i\}_{i=1}^4$, we get $Q = \delta_4[2, 3, 1, 4, 1, 3, 2, 4]$. Let

$$(I_4 \otimes \mathbf{1}_2^T)T = Q,$$

which implies $T = \delta_8[3, 5, 1, 7, 2, 6, 4, 8]$. Thus the logical coordinate transformation $z = Tx$ realizes the maximum decomposition with respect to outputs. It is worth noting that the CC-PEVP is not unique. Another one is $\{\tilde{S}_i\}_{i=1}^4$ with

$$\tilde{S}_1 = \{3, 5\}, \tilde{S}_2 = \{1, 7\}, \tilde{S}_3 = \{2, 4\}, \tilde{S}_4 = \{6, 8\},$$

which results a coordinate transformation matrix $\tilde{T} = \delta_8[3, 5, 1, 6, 2, 7, 4, 8]$. A straightforward computation shows that

$$R = \frac{1}{4}(\mathbf{1}_4^T \otimes I_2)T\tilde{T}^T(\mathbf{1}_4 \otimes I_2) = \frac{1}{4} \begin{bmatrix} 3 & 1 \\ 1 & 3 \end{bmatrix}.$$

Since R is not a logical matrix, by Remark 1, the largest unobservable subspace is not regular.

6 Conclusions

We have studied the decomposition with respect to outputs for BCNs, which is a generalization of the observability decomposition of the traditional linear control theory. Our analysis relies on some equivalent algebraic and graphical conditions for the decomposability with respect to outputs. It has been revealed that a BCN is decomposable with respect to outputs if and only if it has a CC-PEVP. With the observability matrix, an effective approach has been proposed for searching a CC-PEVP. In our future work, the Kalman decomposition without the regularity assumptions will be considered.

References

- Albert, R., & Othmer, H. G.(2003). The topology of the regulatory interactions predicts the expression pattern of the segment polarity genes in *drosophila melanogaster*. *Journal of theoretical biology*, 223(1),1–18.
- Akutsu, T., Hayashida, M., Ching, W., & Ng, M. K. (2007). Control of Boolean networks: hardness results and algorithms for tree structured networks. *Journal of Theoretical Biology*, 244(4), 670–679.
- Borůvka, O. (1974). Foundations of the Theory of Groupoids and Groups, VEB Deutscher Verlag der Wissenschaften, Berlin.
- Cheng, D. (2009). Input-state approach to Boolean networks, *IEEE Trans. on Neural Networks*, 20(3), 512–52.
- Cheng, D., & Qi, H.(2009). Controllability and observability of boolean control networks. *Automatica*, 45(7),1659–1667.
- Cheng, D., & Qi, H.(2010a). A linear representation of dynamics of boolean networks. *IEEE Trans. on Automatic Control*, 55(10),2251–2258.
- Cheng, D., & Qi, H.(2010b). State-space analysis of boolean networks. *IEEE Trans. on Neural Networks*, 21(4),584–594.
- Cheng, D.(2011). Disturbance decoupling of boolean control networks. *IEEE Trans. on Automatic Control*, 56(1),2–10.
- Cheng, D., Li, Z., & Qi, H.(2010). Realization of boolean control networks. *Automatica*, 46(1),62–69.
- Cheng, D., Qi, H., & Li, Z.(2011). *Analysis and control of Boolean networks: a semi-tensor product approach*. Springer.
- Cheng, D. & Zhao, Y.(2011). Identification of boolean control networks. *Automatica*, 47(4),702–710.
- Faure, A., Naldi, A., Chaouiya, C., & Thieffry, D.(2006). Dynamical analysis of a generic boolean model for the control of the mammalian cell cycle. *Bioinformatics*, 22(14),e124–e131.
- Feng, J., Yao, J., & Cui, P.(2012). Singular boolean networks: Semi-tensor product approach. *Science China Information Sciences*, 56(11),1–14.
- Fornasini, E., & Valcher, M. E.(2013a). Observability, reconstructibility and state observers of boolean control networks. *IEEE Trans. on Automatic Control*, 58(6),1390–1401.
- Fornasini, E., & Valcher, M. E.(2013b). On the periodic trajectories of boolean control networks. *Automatica*, 49(5),1506–1509.
- Kauffman, S. A.(1969). Metabolic stability and epigenesis in randomly constructed genetic nets. *Journal of theoretical biology*, 22(3),437–467.
- Laschov, D., & Margaliot, M.(2012). Controllability of boolean control networks via the perron–frobenius theory. *Automatica*, 48(6),1218–1223.
- Laschov, D., Margaliot, M., & Even, G.(2013). Observability of boolean networks: a graph-theoretic approach. *Automatica*, 48(8),2351–2362.

- Li, R., Yang, M., & Chu, T. (2014). State feedback stabilization for probabilistic Boolean networks, *Automatica*, 50(4), 1272–1278.
- Li, F., & Sun, J.(2012). Controllability of higher order boolean control networks. *Applied Mathematics and Computation*, 219(1),158–169.
- Li, H., & Wang, Y.(2012). On reachability and controllability of switched boolean control networks. *Automatica*, 48(11),2917–2922.
- Potůček, R. (2014). Construction of the smallest common coarser of two and three set partitions, *Analele Stiintifice ale Universitatii Ovidius Constanta*, 22(1), 237–246.
- Zhao, Y., Li, Z., & Cheng, D.(2011). Optimal control of logical control networks. *IEEE Trans. on Automatic Control*, 56(8),1766–1776.
- Zou, Y., & Zhu, J. (2014). System decomposition with respect to inputs for boolean control networks. *Automatica*, 50(4), 1304–1309.